



Message Specification

Issue date: 2014-08-25

Version: 2.9.0

MS46 Call-off acknowledgement, Call-off confirmation

EANCOM 1997 ORDRSP

Belongs to business document specification: BDS 6.1.4, 6.1.5

Link to BDS 6.1.4: http://gs1.se/globalassets/esap/esap6/version-2.9/bds_60104_en290.pdf

Link to BDS 6.1.5: http://gs1.se/globalassets/esap/esap6/version-2.9/bds_60105_en290.pdf

For a correct implementation it is required that the Message Specification (MS) is read together with the corresponding Business Document Specification (BDS) and guideline. If the information in the MS differs from the BDS the information in the BDS applies. The examples in every segment must be read independently and not in combination with other examples.

GS1 Sweden ESAP

		Format	Code	Entity
UNA	Service string advice	C		
UNA1	Component data element separator	M an1	:	
UNA2	Data element separator	M an1	+	
UNA3	Decimal notation	M an1	.	
UNA4	Release indicator	M an1	?	
UNA5	Reserved for future use	M an1		
UNA6	Segment terminator	M an1	'	
Example: <i>UNA:+.?'</i>				
UNB	INTERCHANGE HEADER	M		
S001	SYNTAX IDENTIFIER	M		
0001	Syntax identifier	M a4	UNOC UN/ECE level C	
0002	Syntax version number	M n1	3 Version 3	
S002	INTERCHANGE SENDER	M		
0004	Sender identification	M an..35		Global Location Number (GLN)
0007	Partner identification code qualifier	C an..4 R	14 EAN International EAN is now GS1	
S003	INTERCHANGE RECIPIENT	M		
0010	Recipient identification	M an..35		Global Location Number (GLN)
0007	Partner identification code qualifier	C an..4 R	14 EAN International EAN is now GS1	
S004	DATE/TIME OF PREPARATION	M		
0017	Date of preparation	M n6		
0019	Time of preparation	M n4		
0020	Interchange control reference	M an..14		
S005	RECIPIENT'S REFERENCE	C		
0022	Recipient's reference/password	M an..14		
0026	Application reference	C an..14		
0029	Processing priority code	C a1		
0031	Acknowledgement request	C n1		
0032	Communications agreement ID	C an..35		
0035	Test indicator	C n1		
Example: <i>UNB+UNOC:3+7300012550009:14+7350000001204:14+060924:2310+12345+++ +++1'</i>				
UNH	MESSAGE HEADER	M		
0062	Message reference number	M an..14		
S009	MESSAGE IDENTIFIER	M		
0065	Message type identifier	M an..6	ORDRSP Purchase order response message	
0052	Message type version number	M an..3	D Draft version/UN/EDIFACT Directory	
0054	Message type release number	M an..3	96A Release 1996 - A	
0051	Controlling agency	M an..2	UN UN/CEFACT	
0057	Association assigned code	C an..6 R	EAN005 EAN version control number (EAN Code)	
Example: <i>UNH+54321+ORDRSP:D:96A:UN:EAN005'</i>				
BGM	Document type and number	M		
C002	Document/message name	C R		
1001	Document/message name, coded	C an..3 R	231 Purchase order response	
1004	Document/message number	C an..17 R		T0044 Call-off response number
1225	Message function, coded	C an..3 R		T0045 Call-off response status
Example: <i>BGM+231+142345+12'</i>				
DTM	Document date	M		
C507	Date/time/period	M		
2005	Date/time/period qualifier	M an..3	137 Document/message date/time	



Message Specification

Issue date: 2014-08-25

Version: 2.9.0

MS46 Call-off acknowledgement, Call-off confirmation

EANCOM 1997 ORDRSP

Belongs to business document specification: BDS 6.1.4, 6.1.5

Link to BDS 6.1.4: http://gs1.se/globalassets/esap/esap6/version-2.9/bds_60104_en290.pdf

Link to BDS 6.1.5: http://gs1.se/globalassets/esap/esap6/version-2.9/bds_60105_en290.pdf

For a correct implementation it is required that the Message Specification (MS) is read together with the corresponding Business Document Specification (BDS) and guideline. If the information in the MS differs from the BDS the information in the BDS applies. The examples in every segment must be read independently and not in combination with other examples.

GS1 Sweden ESAP

		Format	Code	Entity
2380	Date/time/period	C an..35 R		T0046 Call-off response date
2379	Date/time/period format qualifier	C an..3 R	102 CCYYMMDD	
Example: <i>DTM+137:20071001:102'</i>				
DTM	Planned delivery date	M	D	
C507	Date/time/period	M		
2005	Date/time/period qualifier	M an..3	76 Delivery date/time, scheduled for	
2380	Date/time/period	C an..35 R		T0048 Planned delivery date
2379	Date/time/period format qualifier	C an..3 R	102 CCYYMMDD	
Example: <i>DTM+76:20071001:102'</i>				
FTX	Reason for rejection	C		
4451	Text subject qualifier	M an..3	ACD Reason	
4453	Text function, coded	C an..3 R	3 Text for immediate use	
C107	Text reference	C	R	
4441	Free text, coded	M an..3		T1329 Reason for rejection, code
1131	Code list qualifier	C an..3 N		
3055	Code list responsible agency, coded	C an..3 R		
Example: <i>FTX+ACD+3+002::9SE'</i>				
SG1		C	R	
RFF	Reference to order	M		
C506	Reference	M		
1153	Reference qualifier	M an..3	ON Order number (buyer)	
1154	Reference number	C an..35 R		T0047 Reference to call-off
Example: <i>RFF+ON:12345'</i>				
SG3		C	R	
NAD	Buyer	M		
3035	Party qualifier	M an..3	BY Buyer	
C082	Party identification details	C	R	
3039	Party id. identification	M an..35		T0008 Buyer identification, GLN Global Location Number (GLN)
1131	Code list qualifier	C an..3 N		
3055	Code list responsible agency, coded	C an..3 R	9 EAN (International Article Numbering association) <i>EAN is now GS1</i>	
Example: <i>NAD+BY+7350000001204::9'</i>				
SG3		C	R	
NAD	Supplier	M		
3035	Party qualifier	M an..3	SU Supplier	
C082	Party identification details	C	R	
3039	Party id. identification	M an..35		T0009 Supplier identification, GLN Global Location Number (GLN)
1131	Code list qualifier	C an..3 N		
3055	Code list responsible agency, coded	C an..3 R	9 EAN (International Article Numbering association) <i>EAN is now GS1</i>	
Example: <i>NAD+SU+7300015200000::9'</i>				
SG26		C	R	
LIN	Order line	M		
1082	Line item number	C n..6 R		T0051 Line number
1229	Action request/notification, coded	C an..3 R		T0049 Line status
C212	Item number identification	C		
7140	Item number	C an..35 R		T0154 Trade item identification, GTIN Global Trade Item Number (GTIN)
7143	Item number type, coded	C an..3 R	EU	



Message Specification

Issue date: 2014-08-25

Version: 2.9.0

MS46 Call-off acknowledgement, Call-off confirmation

EANCOM 1997 ORDRSP

Belongs to business document specification: BDS 6.1.4, 6.1.5

Link to BDS 6.1.4: http://gs1.se/globalassets/esap/esap6/version-2.9/bds_60104_en290.pdf

Link to BDS 6.1.5: http://gs1.se/globalassets/esap/esap6/version-2.9/bds_60105_en290.pdf

For a correct implementation it is required that the Message Specification (MS) is read together with the corresponding Business Document Specification (BDS) and guideline. If the information in the MS differs from the BDS the information in the BDS applies. The examples in every segment must be read independently and not in combination with other examples.

GS1 Sweden ESAP

		Format	Code	Entity
1131	Code list qualifier	C an..3	N	
3055	Code list responsible agency, coded	C an..3	R	9 EAN (International Article Numbering association) <i>EAN is now GS1</i>
Example: <i>LIN+9+1+7300015200154:EU::9'</i>				
SG26		C	R	
PIA	Supplier's article number	C		
4347	Product id. function qualifier	M an..3		5 Product identification
C212	Item number identification	M		
7140	Item number	C an..35	R	T0172 Supplier's article number
7143	Item number type, coded	C an..3	R	SA Supplier's article number
Example: <i>PIA+5+131515515:SA'</i>				
SG26		C	R	
PIA	Manufacturer's article number	C		
4347	Product id. function qualifier	M an..3		5 Product identification
C212	Item number identification	M		
7140	Item number	C an..35	R	T1120 Manufacturer's article number
7143	Item number type, coded	C an..3	R	MF Manufacturer's (producer's) article number
Example: <i>PIA+5+113515151:MF'</i>				
SG26		C	R	
PIA	Replacement trade item identification	C		
4347	Product id. function qualifier	M an..3		3 Substituted by
C212	Item number identification	M		
7140	Item number	C an..35	R	T1319 Replacement trade item identification, GTIN
7143	Item number type, coded	C an..3	R	EU
Example: <i>PIA+3+731111111111K:EU'</i>				
SG26		C	R	
PIA	Replacement supplier item number	C		
4347	Product id. function qualifier	M an..3		3 Substituted by
C212	Item number identification	M		
7140	Item number	C an..35	R	T0050 Replacement supplier item number
7143	Item number type, coded	C an..3	R	SA Supplier's article number
Example: <i>PIA+3+1234567:SA'</i>				
SG26		C	R	
PIA	Replacement manufacturer item number	C		
4347	Product id. function qualifier	M an..3		3 Substituted by
C212	Item number identification	M		
7140	Item number	C an..35	R	T1320 Replacement manufacturer item number
7143	Item number type, coded	C an..3	R	MF Manufacturer's (producer's) article number
Example: <i>PIA+3+A234678:MF'</i>				
SG26		C	R	
QTY	Confirmed quantity	C		
C186	Quantity details	M		
6063	Quantity qualifier	M an..3		21 Ordered quantity
6060	Quantity	M n..15		T0054 Confirmed quantity, value
6411	Measure unit qualifier	C an..3		T0055 Unit of measurement for quantity
Example: <i>QTY+21:9:GRM'</i>				



Message Specification

Issue date: 2014-08-25

Version: 2.9.0

MS46 Call-off acknowledgement, Call-off confirmation

EANCOM 1997 ORDRSP

Belongs to business document specification: BDS 6.1.4, 6.1.5

Link to BDS 6.1.4: http://gs1.se/globalassets/esap/esap6/version-2.9/bds_60104_en290.pdf

Link to BDS 6.1.5: http://gs1.se/globalassets/esap/esap6/version-2.9/bds_60105_en290.pdf

For a correct implementation it is required that the Message Specification (MS) is read together with the corresponding Business Document Specification (BDS) and guideline. If the information in the MS differs from the BDS the information in the BDS applies. The examples in every segment must be read independently and not in combination with other examples.

GS1 Sweden ESAP

		Format	Code	Entity
SG26		C	R	
DTM	Planned delivery date for this trade item	C		
C507	Date/time/period	M		
2005	Date/time/period qualifier	M an..3	76 Delivery date/time, scheduled for	
2380	Date/time/period	C an..35 R		T0053 Planned delivery date for this trade item
2379	Date/time/period format qualifier	C an..3 R	102 CCYYMMDD	
Example: <i>DTM+76:20071015:102'</i>				
SG26		C	R	
DTM	Possible delivery date	C		
C507	Date/time/period	M		
2005	Date/time/period qualifier	M an..3	64 Delivery date/time, earliest	
2380	Date/time/period	C an..35 R		T1304 Possible delivery date
2379	Date/time/period format qualifier	C an..3 R	102 CCYYMMDD	
Example: <i>DTM+64:20071101:102'</i>				
SG26		C	R	
QVR	Deviating quantity	C		
C279	Quantity difference information	C		
6064	Quantity difference	M n..15		T0058 Deviating quantity, value
6063	Quantity qualifier	C an..3 R	21 Ordered quantity	
4221	Discrepancy, coded	C an..3 R	CP Shipment partial - considered complete, no backorder	
C960	Reason for change	C		
4295	Change reason, coded	C an..3 R		T0211 Change reason, code
1131	Code list qualifier	C an..3 N		
3055	Code list responsible agency, coded	C an..3	9SE GS1 Sweden	
Example: <i>QVR+9:21+CP+AS'</i>				
SG26		C	R	
QVR	Backordered quantity	C		
C279	Quantity difference information	C		
6064	Quantity difference	M n..15		T0059 Backordered quantity, value
6063	Quantity qualifier	C an..3 R	21 Ordered quantity	
4221	Discrepancy, coded	C an..3 R	BP Shipment partial - back order to follow	
C960	Reason for change	C		
4295	Change reason, coded	C an..3 R		T0211 Change reason, code
1131	Code list qualifier	C an..3 N		
3055	Code list responsible agency, coded	C an..3	9SE GS1 Sweden	
Example: <i>QVR+9:21+BP+Z4::9SE'</i>				
SG31		C	R	
RFF	Reference to order	M		
C506	Reference	M		
1153	Reference qualifier	M an..3	ON Order number (buyer)	
1154	Reference number	C an..35 R		T0047 Reference to call-off
1156	Line number	C an..6 R		T0088 Reference to call-off line
Example: <i>RFF+ON:12345:3'</i>				
UNS	Start of summary	M		
0081	Section identification	M a1	S Detail/summary section separation	
Example: <i>UNS+S'</i>				
CNT	Control total - quantity	C		
C270	Control	M		



Message Specification

Issue date: 2014-08-25

Version: 2.9.0

MS46 Call-off acknowledgement, Call-off confirmation

EANCOM 1997 ORDRSP

Belongs to business document specification: BDS 6.1.4, 6.1.5

Link to BDS 6.1.4: http://gs1.se/globalassets/esap/esap6/version-2.9/bds_60104_en290.pdf

Link to BDS 6.1.5: http://gs1.se/globalassets/esap/esap6/version-2.9/bds_60105_en290.pdf

For a correct implementation it is required that the Message Specification (MS) is read together with the corresponding Business Document Specification (BDS) and guideline. If the information in the MS differs from the BDS the information in the BDS applies. The examples in every segment must be read independently and not in combination with other examples.

GS1 Sweden ESAP

		Format	Code	Entity
6069	Control qualifier	M an..3	1 Total value of the quantity segments at line level in a message	
6066	Control value	M n..18 Example: <i>CNT+1:9'</i>		T0042 Control total, quantities
CNT	Control total - number of lines	C		
C270	Control	M		
6069	Control qualifier	M an..3	2 Number of line items in message	
6066	Control value	M n..18 Example: <i>CNT+2:9'</i>		T0043 Control total, lines
UNT	MESSAGE TRAILER	M		
0074	Number of segments in a message	M n..6		
0062	Message reference number	M an..14 Example: <i>UNT+23+54321'</i>		
UNZ	INTERCHANGE TRAILER	M		
0036	Interchange control count	M n..6		
0020	Interchange control reference	M an..14 Example: <i>UNZ+1+12345'</i>		